

<table border="1"> <tr> <td>Model</td> <td>PBA30F-5</td> </tr> <tr> <td>Item</td> <td>Ripple-Noise</td> </tr> <tr> <td>Object</td> <td>+5V6A</td> </tr> </table>		Model	PBA30F-5	Item	Ripple-Noise	Object	+5V6A	Temperature 25°C Testing Circuitry Figure A																																																											
Model	PBA30F-5																																																																		
Item	Ripple-Noise																																																																		
Object	+5V6A																																																																		
<p>1. Graph</p> <div style="text-align: right;">                     —△— Input Volt. 100V                      -·-○- - Input Volt. 200V                 </div> <table border="1"> <caption>Graph Data (Approximate)</caption> <thead> <tr> <th>Load Current [A]</th> <th>100V Input [mV]</th> <th>200V Input [mV]</th> </tr> </thead> <tbody> <tr><td>0.0</td><td>15</td><td>15</td></tr> <tr><td>1.0</td><td>15</td><td>15</td></tr> <tr><td>2.0</td><td>25</td><td>20</td></tr> <tr><td>3.0</td><td>35</td><td>25</td></tr> <tr><td>4.0</td><td>40</td><td>35</td></tr> <tr><td>5.0</td><td>40</td><td>40</td></tr> <tr><td>6.0</td><td>50</td><td>45</td></tr> <tr><td>6.6</td><td>55</td><td>55</td></tr> </tbody> </table> <p>Measured by 20 MHz Oscilloscope.                      Ripple-Noise is shown as p-p in the figure below.                      Note: Slanted line shows the range of the rated load current.</p>		Load Current [A]	100V Input [mV]	200V Input [mV]	0.0	15	15	1.0	15	15	2.0	25	20	3.0	35	25	4.0	40	35	5.0	40	40	6.0	50	45	6.6	55	55	<p>2. Values</p> <table border="1"> <thead> <tr> <th rowspan="2">Load Current [A]</th> <th colspan="2">Ripple-Noise [mV]</th> </tr> <tr> <th>Input Volt. 100 [V]</th> <th>Input Volt. 200 [V]</th> </tr> </thead> <tbody> <tr><td>0.0</td><td>15</td><td>15</td></tr> <tr><td>1.0</td><td>15</td><td>15</td></tr> <tr><td>2.0</td><td>25</td><td>20</td></tr> <tr><td>3.0</td><td>35</td><td>25</td></tr> <tr><td>4.0</td><td>40</td><td>35</td></tr> <tr><td>5.0</td><td>40</td><td>40</td></tr> <tr><td>6.0</td><td>50</td><td>45</td></tr> <tr><td>6.6</td><td>55</td><td>55</td></tr> <tr><td>--</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td></tr> </tbody> </table>	Load Current [A]	Ripple-Noise [mV]		Input Volt. 100 [V]	Input Volt. 200 [V]	0.0	15	15	1.0	15	15	2.0	25	20	3.0	35	25	4.0	40	35	5.0	40	40	6.0	50	45	6.6	55	55	--	-	-	--	-	-	--	-	-
Load Current [A]	100V Input [mV]	200V Input [mV]																																																																	
0.0	15	15																																																																	
1.0	15	15																																																																	
2.0	25	20																																																																	
3.0	35	25																																																																	
4.0	40	35																																																																	
5.0	40	40																																																																	
6.0	50	45																																																																	
6.6	55	55																																																																	
Load Current [A]	Ripple-Noise [mV]																																																																		
	Input Volt. 100 [V]	Input Volt. 200 [V]																																																																	
0.0	15	15																																																																	
1.0	15	15																																																																	
2.0	25	20																																																																	
3.0	35	25																																																																	
4.0	40	35																																																																	
5.0	40	40																																																																	
6.0	50	45																																																																	
6.6	55	55																																																																	
--	-	-																																																																	
--	-	-																																																																	
--	-	-																																																																	
<div style="text-align: center;"> <p>T1: Due to AC Input Line                          T2: Due to Switching</p> <p>Ripple-Noise [mVp-p]</p> </div> <p>Fig. Complex Ripple Wave Form</p>																																																																			

<table border="1"> <tr> <td>Model</td> <td>PBA30F-9</td> </tr> <tr> <td>Item</td> <td>Ripple-Noise</td> </tr> <tr> <td>Object</td> <td>+9V3.4A</td> </tr> </table>		Model	PBA30F-9	Item	Ripple-Noise	Object	+9V3.4A	Temperature 25°C Testing Circuitry Figure A																																
Model	PBA30F-9																																							
Item	Ripple-Noise																																							
Object	+9V3.4A																																							
<p>1. Graph</p> <div style="text-align: right;">                     —△— Input Volt. 100V                      - - ○ - - Input Volt. 200V                 </div> <p>Measured by 20 MHz Oscilloscope.                  Ripple-Noise is shown as p-p in the figure below.                  Note: Slanted line shows the range of the rated load current.</p>		<p>2. Values</p> <table border="1"> <thead> <tr> <th rowspan="2">Load Current [A]</th> <th colspan="2">Ripple-Noise [mV]</th> </tr> <tr> <th>Input Volt. 100 [V]</th> <th>Input Volt. 200 [V]</th> </tr> </thead> <tbody> <tr><td>0.00</td><td>25</td><td>25</td></tr> <tr><td>0.60</td><td>30</td><td>25</td></tr> <tr><td>1.20</td><td>30</td><td>30</td></tr> <tr><td>1.80</td><td>35</td><td>30</td></tr> <tr><td>2.40</td><td>35</td><td>30</td></tr> <tr><td>3.00</td><td>40</td><td>30</td></tr> <tr><td>3.40</td><td>45</td><td>35</td></tr> <tr><td>3.74</td><td>50</td><td>40</td></tr> <tr><td>-</td><td>-</td><td>-</td></tr> <tr><td>-</td><td>-</td><td>-</td></tr> <tr><td>-</td><td>-</td><td>-</td></tr> </tbody> </table>	Load Current [A]	Ripple-Noise [mV]		Input Volt. 100 [V]	Input Volt. 200 [V]	0.00	25	25	0.60	30	25	1.20	30	30	1.80	35	30	2.40	35	30	3.00	40	30	3.40	45	35	3.74	50	40	-	-	-	-	-	-	-	-	-
Load Current [A]	Ripple-Noise [mV]																																							
	Input Volt. 100 [V]	Input Volt. 200 [V]																																						
0.00	25	25																																						
0.60	30	25																																						
1.20	30	30																																						
1.80	35	30																																						
2.40	35	30																																						
3.00	40	30																																						
3.40	45	35																																						
3.74	50	40																																						
-	-	-																																						
-	-	-																																						
-	-	-																																						
<p>T1: Due to AC Input Line                  T2: Due to Switching</p> <p>Ripple-Noise [mVp-p]</p>																																								
<p>Fig. Complex Ripple Wave Form</p>																																								

<p>Model PBA30F-12</p> <p>Item Ripple-Noise</p> <p>Object +12V2.5A</p>		<p>Temperature 25°C</p> <p>Testing Circuitry Figure A</p>																																						
<p>1. Graph</p> <div style="text-align: right;"> <p>—△— Input Volt. 100V</p> <p>- -○- - Input Volt. 200V</p> </div> <p>Measured by 20 MHz Oscilloscope. Ripple-Noise is shown as p-p in the figure below. Note: Slanted line shows the range of the rated load current.</p>		<p>2. Values</p> <table border="1"> <thead> <tr> <th rowspan="2">Load Current [A]</th> <th colspan="2">Ripple-Noise [mV]</th> </tr> <tr> <th>Input Volt. 100 [V]</th> <th>Input Volt. 200 [V]</th> </tr> </thead> <tbody> <tr><td>0.00</td><td>25</td><td>25</td></tr> <tr><td>0.40</td><td>35</td><td>30</td></tr> <tr><td>0.80</td><td>35</td><td>30</td></tr> <tr><td>1.20</td><td>45</td><td>30</td></tr> <tr><td>1.60</td><td>50</td><td>35</td></tr> <tr><td>2.00</td><td>60</td><td>40</td></tr> <tr><td>2.40</td><td>65</td><td>45</td></tr> <tr><td>2.50</td><td>70</td><td>50</td></tr> <tr><td>2.75</td><td>75</td><td>60</td></tr> <tr><td>-</td><td>-</td><td>-</td></tr> <tr><td>-</td><td>-</td><td>-</td></tr> </tbody> </table>	Load Current [A]	Ripple-Noise [mV]		Input Volt. 100 [V]	Input Volt. 200 [V]	0.00	25	25	0.40	35	30	0.80	35	30	1.20	45	30	1.60	50	35	2.00	60	40	2.40	65	45	2.50	70	50	2.75	75	60	-	-	-	-	-	-
Load Current [A]	Ripple-Noise [mV]																																							
	Input Volt. 100 [V]	Input Volt. 200 [V]																																						
0.00	25	25																																						
0.40	35	30																																						
0.80	35	30																																						
1.20	45	30																																						
1.60	50	35																																						
2.00	60	40																																						
2.40	65	45																																						
2.50	70	50																																						
2.75	75	60																																						
-	-	-																																						
-	-	-																																						
<p>T1: Due to AC Input Line T2: Due to Switching</p> <p>Ripple-Noise [mVp-p]</p> <p>Fig. Complex Ripple Wave Form</p>																																								